

PAVA

Panasonic Voice Alarm System



Features

- › 4, 8, or 16 speaker lines
- › 320W, 640W, or 1500W total power (rms)
- › 1, 2, or 3 simultaneous messages
- › Software Integration with Panasonic EBL Fire Alarm System via Gateway
- › Integration with SIP and IP Intercom
- › Easy integration with building- and security management systems
- › Easy and flexible commissioning and maintenance

General

- › Tested and approved according to EN54-16 and EN54-4
- › CPR: 1438-CPR-1146

Order number

- › PAVA - 2001 (L, LN)*
- › PAVA - 4001 (L, LN)*
- › PAVA - 4002 (L, LN, LNR)*
- › PAVA - 8002 (L, LN, LNR, R)*
- › PAVA - 8003 (LN, LNR, R)*

* L: Touch screen display, N: Built in network switch, R: Rack mounted

Related products

- › 5088 - Gateway
- › PAVA-DFMS - Fireman's microphone
- › PAVA-DMS - Zone microphone
- › PAVA-DMS-LCD - Zone microphone with LCD
- › PAVA-EKB-20M - Microphone keyboard extension
- › ABT-EOL - End of line supervision module
- › ABT-REG - Volume Controller
- › GS110TP - Network Switch



Wall: 30 to 34 kg
Rack: 16 to 20 kg



Wall: 797 x 442 x 241 mm
Rack: 176 x 440 x 354 mm



Wall: 55Ah
Rack: 65Ah



IP30



-5 TO +40 °C



230 V AC



<95%

